

# Product datasheet

Specifications



plain text display terminal, Altivar,  
128 x 64pixels, IP21

VW3A1113

## Main

Range of product	Altivar
Range compatibility	Easy Altivar 610 Altivar Machine ATV340
Accessory / separate part category	Display and signalling accessories
Accessory / separate part type	Display terminal
Accessory / separate part destination	Variable speed drive
Product specific application	To control, adjust and configure the drive To display the current values To save and download configurations
IP degree of protection	IP21

## Complementary

User language	French German English Spanish Italian Chinese
Realtime clock	Without
Display type	Backlit LCD screen white
Messages display capacity	2 lines
Pixel resolution	128 x 64
Net weight	0.05 kg

## Environment

Ambient air temperature for operation	-15...50 °C
---------------------------------------	-------------

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	5.700 cm
Package 1 Width	9.200 cm
Package 1 Length	12.400 cm
Package 1 Weight	99.000 g
Unit Type of Package 2	S03

<b>Number of Units in Package 2</b>	45
<b>Package 2 Height</b>	30.000 cm
<b>Package 2 Width</b>	30.000 cm
<b>Package 2 Length</b>	40.000 cm
<b>Package 2 Weight</b>	5.360 kg

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

Total lifecycle Carbon footprint 51

Environmental Disclosure [Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard No

Packaging without single use plastic Yes

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

SCIP Number 1e93978f-15df-45bb-af19-570d1473ed50

REACH Regulation [REACH Declaration](#)

## Use Again

### Repack and remanufacture

End of life manual availability No need of specific recycling operations

Take-back No